

### Abstract of the Disclosure

A SAR radar avoids the need for an INS/GPS by focusing a SAR image having discernible features and a center. The image is formed from digitized returns, each of said digitized returns having a phase and an amplitude. The focusing steps are:

- storing digitized returns acquired in an azimuth and a range coordinate system;
- 5 searching within said memory for returns descriptive of the features;
- computing a coarse range and coarse range rate of the center of said image from the change in position of the features within the azimuth and range coordinate system;
- motion compensating the digitized returns forming the image using the coarse
- 10 range and coarse range rate to form a coarse image;
- converting the digitized returns in polar format into an orthogonal Cartesian coordinate system where the digitized returns are adjusted in phase and amplitude to form an evenly spaced image data ;
- autofocusing the evenly spaced image data to obtain a focused image;
- 15 performing a two dimensional Fourier transform to obtain a focused image described by the returns;
- testing the focused image for a focus quality ;
- computing an estimated (fine) range and (fine) range rate from features contained within the focused image;
- 20 converting the fine range and fine range rate within the orthogonal Cartesian coordinate system for use within the azimuth and range coordinate system and motion compensating the digitized returns;
- iterating the motion compensating step and subsequent steps using the fine range and the fine range rate until the attributes of focus quality reach a predefined
- 25 level.

The autofocus step generates a phase error, said phase error is converted to an adjustment to said fine range. The adjustment is fed back to the motion compensating step.